



PANEL MTG. DETAIL

SPECIFICATIONS												
WIRING	INPUT		OUTPUT				SHAFT ROTATION TO INCREASE VOLTAGE	TERMINAL CONNECTION				
	VOLTS	HERTZ	CONSTANT CURRENT LOAD		CONSTANT IMPEDANCE LOAD			FOR INCREASING VOLTAGE AS VIEWED FROM BASE END				
			MAX. AMPS	MAX. KVA	MAX. AMPS	MAX. KVA		INPUT	JUMPER	OUTPUT		
SINGLE PHASE	120	50/60	0—120	1.75	0.21	2.2	0.26	CW	1—2	—	1—3	
		60	0—132	1.75	0.23	—	—	CCW	1—2	—	2—3	
								CW	1—4	—	1—3	
UNLESS OTHERWISE SPECIFIED, TOLERANCE IS ± DECIMALS HOLES ANGLES DRAFT .XX .0006 .06 .002 1° 1-1/2° .XXX .005			UNITS IN [mm]		TITLE: SPEC. CONTROL DRAWING VARIABLE TRANSFORMER MODEL 171							
MATERIAL :			ALL DIMENSIONS APPLY AFTER PLATING									
The information and design disclosed herein was originated by and is the property of STACO ENERGY PRODUCTS CO., which reserves all patent, proprietary, design, manufacturing, reproduction, use and sale rights thereto, and to any article disclosed therein except to the extent rights are expressly granted to others. The foregoing does not apply to vendor proprietary parts.					DRAWN BY S.A. SMITH		DATE 1/30/02		FIRST USED ON		DO NOT SCALE DWG.	
					CHECKER SAS		DATE 1/30/02		WEIGHT APPROX.		CASE CODE 83008	
					ENGINEER SAS		DATE 1/30/02		SCALE 1/1		SHEET 1 of 1	
											DWG. SIZE D 031—0101	

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Staco:

171